


CBI1235A

12 V 35 A Intelligent Battery Charger & Power Supply Unit

CoolPower
Solutions

- Single Phase Input 90-135 VAC / 180-305 VAC, 47-63 Hz
- Output 1: Load power supply 12 VDC, 35 A
- Output 2: Battery charging 12 VDC, 35 A
- Suited for the following battery types: Open Lead Acid, Sealed Lead Acid, lead Gel and Ni-Cd (option)
- Automatic diagnostic of battery status. Charging curve IUoUo, constant voltage and constant current Battery Life Test function
- Switching technology, output voltage 10,4-14,4 VDC
Three charging levels: Boost, Trickle and Recovery
- Protected against short circuit and inverted polarity
- Signal output (contact free) for discharged or damaged battery
- Signal output (contact free) for mains or Back-up
- Protection degree IP20 - DIN rail; Space saving



Technical features

Thanks to the All-In-One units (DC-UPS), it will be possible to optimize power management. The available power is automatically allocated between load and battery, supplying power to the load is the first priority of the unit thus it is not necessary to double the power, because also the power going to the battery will go to the load if the load so requires. The maximum available current on the load output is 2 times the value of the device rated current I_n .

We call "Battery Care" the concept base on algorithms that implement rapid and automatic charging, battery charge optimization during time, flat batteries recovery and real time diagnostic during installation and operation. The Real Time Auto-diagnostic system, monitoring battery faults such as, battery Sulfated, elements in short circuit, accidental reverse polarity connection, disconnection of the battery, they can easily be detected and removed by help of Blink Code of Diagnosis Led; during the installation and after sell. The continuous monitoring of battery efficiency, reduces battery damage risk and allows a safe operation in permanent connection.

Each device is suited for all battery types, by means of jumpers it is possible setting predefined curves for Open Lead Acid, Sealed Lead Acid, Gel, Ni-Cd (option). They are programmed for two charging levels, boost and charge, but they can be changed to single charging level by the user.

A rugged casing with bracket for DIN rail mounting provide IP20 protection degree. They are extremely compact and cost-effective.

Electrical specifications

Model No.		CBI1235A
Input	Voltage	90 ~ 135 VAC or 180 ~ 305 VAC
	Frequency	47-63 Hz
	Current	8,0 A (115 VAC) / 4,2 A (230 VAC)
	Inrush Current	$\leq 35 \text{ A } \leq 5 \text{ ms}$
	Internal fuse	10 A (not replaceable)
	External Fuse	16 A (recommended) MCB curve B
Output (Power Supply)	Voltage (nominal)	12 VDC
	Current (nominal)	35 A
	Efficiency	$\geq 91\%$ (at 50% of rated current)
	Turn-On delay	1,0 s max after applying mains voltage
	Start up with strong load	Yes, unlimited (Capacitive load)
	Dissipation power load	48 W max
	Short-circuit protection	Yes
	Over Load protection	Yes
	Over Voltage protection	Yes (typ. 35 VDC)
Overheating protection	Yes	

Output (Battery)	Boost charge	14,4 VDC (25 °C) (at In)
	Max. time Boost Charge	15 h
	Min. time Boost Charge	1 min
	Trickle charge	13,75 VDC (25 °C) (at In)
	Jumper Configuration battery type	Lead Acid: 2,23; 2,25; 2,27; 2,30 V/cell Optional NiCd:1,5 V/cell (10 elem.)
	Recovery Charge	2 – 9 VDC
	Charging current	35 A ±5% max
	Charging current limiting	10 - 100 % / Ibat (adjustable)
	Reverse battery protection	Yes
	Sulfated battery check	Yes by Jumper
	Detection of element in short circuit	Yes
	Quiescent Current	≤100 mA max
	Charging Curve	3 stage automatic: IUoUo
	Remote Input Control	Boost /Trickle via RTCONN cable
Output (Load)	Output voltage	10 – 14,4 VDC (17 VDC for NiCd)
	Nominal current	1.1 x In A ± 5%
	Continuous current	Without battery 35 A
		With battery 70 A
	Max current output	Main 105 A max Iload (4 sec.)
		Backup 70 A max Iload (4 sec.)
	Remote Input Control	Start from battery without main via RTCONN cable
	Time Buffering	0.5; 1; 3; 5; 10; 15; 20; 30; 45; 60; ∞ min. (switch output off without main input)
Protections	9 – 10 Vdc batt Against total discharge	
Threshold alarm	10 – 11 Vdc batt Battery almost flat	
Signals	Signal Output	Free switch contacts: Main or Backup Power, Low Battery, Fault Battery
	Type of Signal Output	Max. Current can be switched (EN60947.4.1): Resistive load
		Max. DC1: 30 Vdc 1 A; AC1: 60 Vac 1A, Min.1mA at 5 Vdc Min permissive load
Signal Input / Output	(RJ45) Temp. Comp. Battery (with external probe), Remote monitoring display CAN Bus optional	
Environment	Operating Temperature	-25°C...+70°C (with derating T>50°C -2.5%(In) / °C)
	Storage Temperature	-40°C...+85°C
	Humidity	20 - 95% RH to 25°C
	Cooling	Auto convention
General data	Insulation voltage	3000 VAC (I/O), 1605 VAC (I/Gr), 500 VAC (O/Gr)
	Protection Class	IP20, (EN/IEC 60529)
	Reliability: MTBF	>300 000 h (IEC 61709)
	Pollution Degree	2
	Connections	Terminal Blocks screw Type; 4mm (30–10AWG)
	Protection class	I, with PE connected
	Dimension (W x H x D)	150 x 115 x 135 mm
Weight	1550 g	
Norms and Certifications	In Conformity to: IEC/EN 60335-2-29 Battery chargers; EN60950 / UL60950-1 and CSA C22.2 No. 60950-1-07 (Information Technology Equipment) – Safety – Part1:General Requirement. Electrical safety; EN54-4 Fire Detection and fire alarm systems; 89/336/EEC EMC Directive; 2014/35/UE (Low Voltage); DIN41773 (Charging cycle); Emission: IEC 61000-6-3; Immunity: IEC 61000-6-2. CE.	